

Application note 00001

CM-iGLX BIOS SUPPORT FOR NON STANDARD LCD

Starting from BIOS version from 09-01-2007 there is incorporated support for the non-standard LCD resolution. To use it enter the BIOS ->"Custom Configuration"->"LCD device mode"->choose wanted resolution by width(i.e if you want 800x480 you should choose 800x600) and then appropriate ratio from "LCD Wide Screen" menu(5:3,16:9,16:10,Disabled).

For example if the base resolution is 800x600 then

- choosing 5:3 ratio will lead to actual 800x480 resolution.
- choosing 16:9 ratio will lead to actual 800x450 resolution.
- choosing 16:10 ratio will lead to actual 800x500 resolution.

You can choose desired resolution from the table below

<i>Resolution/Ratio</i>	<i>640x480</i>	<i>800x600</i>	<i>1024x768</i>	<i>1152x864</i>	<i>1280x1024</i>	<i>1600x1200</i>
Disabled	640x480	800x600	1024x768	1152x864	1280x1024	1600x1200
5:3	640x384	800x480	1024x614	1152x692	1280x768	1600x960
16:9	640x360	800x450	1024x576	1152x648	1280x720	1600x900
16:10	640x400	800x500	1024x640	1152x720	1280x800	1600x1000